

## DS-PM1-I1-WB



DS-PM1-I1-WB wireless single input transmitter offers a connection of third party wired detectors like outdoor PIR, to AX PRO alarm system. The alarm types and zone parameters can be set through APP by installers easily, small size design is convenient for installation. Also, transmitter has a feature of detecting device removal by accelerometer application, if someone moves the detector away, an alarm will be reported immediately.

- Small size design, which can be put into wired detector easily
- 433MHz two-way wireless communication
- LED display, show the real status of device
- With one tamper input and one PGM, can be used as zone input or alarm output
- With 3.3v voltage output, can be used to power up external wired detector
- Detection of device removal by accelerometer

## ▪ Specification

Hardware features	
Serial port	1
Power switch	1
Alarm input	1 Alarm, 1 Tamper
Alarm output	1 PGM, AM/Output
3.3v Output	1, up to 10mA
Electrical characteristics	
Power supply	3 CR123
Operation humidity	10%~90%
Operation temperature	-10°C ~ 55°C
Power consumption	Quiescent current: 40.29 uA Max current: 47.85mA Voltage: 3 VDC
Battery life span	Up to 5 years (standby time)
Wireless transmission	
RF frequency	433MHz
RF method	Two-way communication
RF modulation	2GFSK
RF distance	1300m
Display	
Indicator	3: Alarm/Tamper (Red) , Fault (Amber) , Signal Strength (Green/Red)
General	
Installation method	Put inside Wireless Ready Detector
Dimension(WxHxD)	102*41*20mm
Weight	35g(Without Battery), 90g(With Battery)

## ▪ Available Model

DS-PM1-I1-WB

**Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
www.hikvision.com



Follow us on social media to get the latest product and solution information.

